Media: air - water - gases - liquid Pressure range: 0 to 10 Bar max *Media temperature: -15°C +100°C max* Ambient temperature: -15°C to +50°C Media viscosity: 500 centistokes max

Duty cycle: 100,000 Mounting: Any Seals: PTFE/ FKM

### Actuated Ball Valve

3 WAY Brass L + T Ported 0 - 10 Bar





	PRESSURE									
Ø	Orifice mm	Operating Time Seconds	Pressure Rating (Bar) $\Delta P$							
Port BSP			Min	Max	Voltage	Part Number				
1/4		5	0	10	9 to 24v AC or DC	ABVM02B3(L or TA, B, D or E)/9AR				
1/4	6	o	0	10	110 to 240vAC	ABVM02B3(L or TA, B, D or E)/2AR				
3/8	6	5	0	10	9 to 24v AC or DC	ABVM03B3(L or TA, B, D or E)/9AR				
3/6					110 to 240vAC	ABVM03B3(L or TA, B, D or E)/2AR				
1/2	12	5	0	10	9 to 24v AC or DC	ABVM04B3(L or TA, B, D or E)/9AR				
1/2	12	3	5	U	10	110 to 240vAC	ABVM04B3(L or TA, B, D or E)/2AR			
3/4	15	5	0	10	9 to 24v AC or DC	ABVM06B3(L or TA, B, D or E)/9AR				
3/4	15	5	0	10	110 to 240vAC	ABVM06B3(L or TA, B, D or E)/2AR				
4	18	5	0	10	9 to 24v AC or DC	ABVM08B3(L or TA, B, D or E)/9AR				
	10	ິວ	0	10	110 to 240vAC	ABVM08B3(L or TA, B, D or E)/2AR				

### **OPTIONS**


Visual Position Indication, Failsafe (2 wire) or Power Open/Close (3-wire), L or T Ported (T port 4 configuration options A, B, D or E) Manual Over Ride (Lift + Turn +MO) 9-24 volt only.


3 wire control (power open and power close - stay put with power off)


Fully Open and fully closed position volt free feedback switches (+E2)

	ı	r	1	С	ı	u	a	е	α	

ELECTRICAL DATA								
Voltage Min - Max	Actuator		Power			Enclosure	Electrical connections	
Continuous Duty 100%	Model	Torque	Start (Peek)	Moving	Holding	Eliciosure	Electrical confilections	
9 to 24 volts AC 50/60Hz or DC	ABVM	2 Nm	2 Amp	5 Watts	0.22 Watts	IP67	0.5 meter lead wires 3 meter lead wires	
110 to 240 volts AC 50/60Hz			0.5 Amp		0.6 Watts			







### Failsafe Control.

Power ON motor actuates valve into powered position and then automatically powers off. Valve stays in powered position.

Power OFF motor actuates valve back to start position using reserve power. Valve stays in start position.


Requires 30 seconds power On to recharge the Farah capacitors.


#### 3 Wire Control

Power ON to GREEN motor actuates valve into powered position and then automatically powers off. Valve stays in powered position

Power OFF to GREEN motor actuates valve back to start position and then automatically powers off. Valve stays in start position.

## With Position Feed Back Switches







### CONSTRUCTION

Valve Body: Brass, Seals: FKM & PTFE Floating no leakage design

ABVM Actuator: ABS Engineering Plastic, Gears Metal

### OVERALL DIMENSIONS





# Pattern Power On Power Off

Port	đ	L1	L2/L3	E1	H1	H2
1/4	6	51	11	20.2	66	11
3/8	6	51	11	20.2	66	11
1/2	12	70	16	27	72	17
3/4	15	75	16	31	76.5	20.5
1	18	85	17	38	78	22.5

No.	Description	Material
1	Actuator	ABS
2	Body Cover	Brass
3	O Ring	FKM
4	Sealing	PTFE
5	Ball	SS304
6	Stem	Brass
7	O Ring	FKM